

Water-proof cover

Flange nut


Instruction:

1/ Wiper motor WEM2060, 24V, 70W, anode control 5 wires.


2/ Wiper angle 80°.

3/ Material of output shaft is stainless steel,  
Material of shaft housing is brass.

Circuit diagram



Motor plug  
(Model: DJ7061-6.3-11)



Nominal voltage		24V
Test voltage		27V
Brake torque		35N.m
Working torque		9N.m
Noise		≤ 50dB(A)
No-load speed	L-speed	30 ± 5rpm
	H-speed	45 ± 5rpm
No-load current	L-speed	≤ 1.5A
	H-speed	≤ 2A

Date  
2008.08.16

Edt	Mark	Signature	Date	Wiper motor assembly		Customer	Osculati S.P.A	
Design		Zou Hongwei	2008.08.15	Weight		Model	19 185 02	
Proofread		He Guozhong	2008.08.16	View		Drawing #		
Review		Zhang Ming	2008.08.16	Scale	1:1	Edition	A	Pages
Approval		Chen Linbin	2008.08.16					